

To install the Universal Cable Lock Kit:



- Determine a secure fixture which you can wrap the security cable around or through. Be sure this point is close enough so the security cable can reach your device's security slot.
- Suggested secure fixture:
 - A cable pass-through hole in the top of the desk
 - The portion of a table leg between the supporting cross bar and the table top
 - An attached Desktop Anchor Point (photo 1) [SecurTech item: DAP]
- Wrap the cable around or through the secure fixture and pass one end of the cable through the loop in the other end of the cable. Pull it all the way through until it is snug.
- Expand the Scissor Clip so that the two small L-shaped ends overlap each other. Insert the overlapping ends into your device's security slot (photo 2).
- Squeeze the Scissor Clip together so the L-shaped ends expand inside the security slot and the holes in both halves of the Scissor Clip are aligned. Be certain it is securely fitted into the security slot.
- Take the Scissor Clip Insert (the square metal fitting with the round hole in it) and insert it into the Scissor Clip's slot (photo 3).
- Feed the security cable through the hole in the Scissor Clip Insert and then into the locking head's rectangular hole (photo 4). To lock it, push the button on the end of the locking head. To unlock it, insert the key into the locking head and turn it one full revolution.

Thank you for choosing SecurTech.

To secure additional devices:

You can secure multiple devices with a single ULK610 cable. The cable can pass through multiple Scissor Clips and Spot Anchors between the secure fixture at one end of the cable and the locking head at the other end of the cable.



Scissor Clips are used to secure devices that have a standard built-in security slot. A Scissor Clip comes with a Scissor Clip Insert. One set ships with each ULK610. Additional sets are sold separately. (SecurTech item: USC1)



Spot Anchors are used to secure devices that do not have a standard built-in security slot. Spot Anchors are available in multiple sizes and cable lengths. Sold separately. (SecurTech item: AL)



The Desktop Anchor Point can be mounted to a wood surface to create a secure fixture where no other option is available. Sold separately. (SecurTech item: DAP)



Another installation option is to create a cable end-loop by passing the cable through the hole in the locking head of the ULK610 and then locking the head to the tip of the cable.



The finished installation might look like this: The cable is secured through the hole in the desk. The cable then passes through the Scissor Clip in the monitor, then through the Scissor Clip in the PC, and then the locking head is secured to the cable tip.